

NOTE: If microphone is powered off or the link is lost the BTA will power down after 5 minutes. To re-establish link while the microphone is back on, short press the PTT button on the BTA until LED appears. At this time both units will auto pair.



ⓘ To secure the BTA dongle, wrap the Velcro strap around radio antennae.

BLUETOOTH VERSION	4.0 V
CHIP	CSR8670
BLUETOOTH RANGE	10 METERS
FREQUENCY	2.4 G
RF FREQUENCY	CLASS 2
TRANSMITTED POWER	6 dB
SENSITIVITY	-80 dB
STANDBY TIME	SAVE MODE 100 HOURS, FAST RESPONSE 9 HOURS
WORKING TIME	ABOUT 9 HOURS
CHARGING TIME	ABOUT 3 HOURS
BATTERY TYPE	200 mAh LITHIUM-ION POLYMER RECHARGEABLE BATTERY
WORKING VOLTAGE	3.3 - 4.2 V

MANUFACTURER’S LIMITED WARRANTY

Your **SALES RECEIPT** is required to validate & obtain warranty services.

Your Tactical Ear Gadget is warranted against internal defects in material or workmanship. All of our earphones are warranted for 12 months. Hygiene restrictions prevent us from extending our limited warranty to wearable parts such as: Torpedoes, Fins, foam pads, clear tubes & ear inserts.

The warranty is extended to the original purchaser only and does not cover the following:

- * Physical abuse
- * Damage from tugging or pulling
- * Improper maintenance of unit
- * Frayed, torn or exposed wires
- * Crushing or smashing in any way, shape or form

General misuse of the item such as: Excessive voltage, tampering with the unit or repairs attempted by someone other than the manufacturer will void the MANUFACTURER’S LIMITED WARRANTY.

The manufacturer reserves the right to evaluate and refuse warranty based on their evaluation. In order to obtain warranty services, proof of purchase in the form of a SALES RECEIPT **must** be returned along with the product.

For Returns Dept. Call Toll Free: (888) 372-1888



BTA-01

BLUETOOTH DONGLE MANUAL



BTA PAIRING INSTRUCTIONS:

STEP #1:

First connect the BTA dongle to the USB cable. Make sure the USB cable is plugged in to the charger. The LED will flash Red.



Press the PTT button on the BTA until LED is flashing Blue/Red then release.

STEP #2:

On the Bluetooth microphone press the power button until LED is flashing Blue/Red release then quick press the main PTT on the microphone. This will change the LED pattern & allow the BTA to link to the Bluetooth microphone.



For Interceptor Bluetooth Speaker Microphone, the same pairing process applies.

STEP #3:

When both LED's are Blue, pairing is complete.



Disconnect the BTA from the USB. Upon doing so the BTA will power down. Short press the PTT button on the BTA until first LED appears then release. This will re-establish the link with the Bluetooth microphone.

You can also press the PTT button on the BTA to transmit.

ON/OFF INSTRUCTIONS:

ON: Press and hold the PTT button to turn on the BTA until first LED appears, then release. Press the Power button to turn on Bluetooth microphone until first LED appears, then release. When BTA LED is solid Blue, link is established. You can use the unit.

OFF: First, turn off Bluetooth microphone by pressing the Power button until LED flashes red, then release. Then, turn off BTA by pressing the PTT button until LED flashes red, then release. Now units are powered off.

CHARGING:

Connect USB cable to the BTA and the other end to the wall charger. The unit will flash RED. When solid Red appears unit is charged.